

# NetworX NX8E Addendum

Checksum 7354 dated 26-June-2002

## I. PROGRAMMING CHANGES

### I.A. *Features*

1. Added *NIGHT* mode support for the NX1208E LED keypads and NX1248E LCD keypads. In this mode the NX8E will bypass all zones that have the Entry Guard enabled.

<b>Location 23</b>	<b>Segment 2</b>	<b>Option 8</b>	<b>Manual pages 17, 47</b>
	On enables <i>INSTANT</i> mode toggle		

<b>Location 23</b>	<b>Segment 4</b>	<b>Option 3</b>	<b>Manual pages 17, 47</b>
	ON disables the door delays in <i>NIGHT</i> mode		

2. Added CLEAN ME feature

<b>Location 37</b>	<b>Segment 6</b>	<b>Option 6</b>	<b>Manual pages 22, 49</b>
	On disables the <i>CLEAN ME</i> report		

### I.B. *Zone Configurations*

<b>Location 111</b>	<b>Segment 4</b>	<b>Option 3</b>	<b>Manual pages 32, 58</b>
Access Control	Works in conjunction with Access Control module to delay alarm activation for 60 seconds. <b>NOTE:</b> Do not enable this option unless configured with Access Control module.		

<b>Location 111</b>	<b>Segment 4</b>	<b>Option 4</b>	<b>Manual pages 32, 58</b>
Request to Exit Zone	Works in conjunction with Access Control module to cause this zone to act as a <i>request to exit</i> input. Enabling this option will disable it for alarm activation.		

### I.C. *Auxiliary Output Events*

Added following events:

<b>69</b>	Forced Door Alarm
<b>70</b>	Forced Door Restore